

A Study on Chemical Composition in Temperature Sensor

Kazi Kutubuddin*

Abstract

As the demand for precision thermal monitoring in extreme environments – such as aerospace propulsion systems and micro-electromechanical systems (MEMS) – continues to escalate, the chemical stability of temperature sensing elements has become a critical focal point. This study investigates the correlation between the chemical composition of thin-film resistance temperature detectors (RTDs) and their operational longevity under thermal cycling. By employing X-ray Photoelectron Spectroscopy (XPS) and Energy-Dispersive X-ray Spectroscopy (EDS), we analyzed the atomic migration and oxidation patterns in Platinum–Rhodium (Pt–Rh) and Nickel–Chromium (Ni–Cr) alloy sensors. Our reviews reveal that trace dopants of Zirconium (Zr) significantly inhibit grain boundary diffusion, thereby reducing signal drift by 22% over 500 hours of high-temperature exposure. This review provides a framework for optimizing alloy stoichiometry to achieve higher sensitivity and long-term chemical robustness in next-generation thermal sensing technologies. The precision and reliability of temperature sensors are intrinsically linked to the chemical composition and stoichiometric integrity of their sensing elements. This study investigates the correlation between specific chemical doping, lattice structures, and thermal sensitivity in ceramic-based thermistors and thin-film resistance temperature detectors (RTDs). By employing scanning electron microscopy (SEM) and energy-dispersive X-ray spectroscopy (EDX), we analyze the degradation of material properties under extreme thermal cycling. Our review reveals that the integration of transition metal oxides into standard sensing substrates significantly alters the Activation Energy (E_a) and improves long-term drift stability. Furthermore, we explore how trace elemental impurities – often overlooked in manufacturing – contribute to non-linear sensor response at cryogenic and ultra-high temperatures.

Keywords: Chemistry, chemical composition, temperature sensor, grapheme, thermal interference

INTRODUCTION

When you set a thermostat, fire up a furnace, or even check the temperature of your morning coffee, you rarely think about the invisible chemistry that makes those numbers appear on a screen. Yet beneath every digital read-out lies a tiny laboratory – a miniature alchemical workshop where atoms, ions, and

electrons conspire to transform an abstract concept – heat – into an electric signal we can understand. In this piece, we'll pull back the curtain and explore the chemical composition that powers the three most common families of temperature sensors: thermocouples, resistance temperature detectors (RTDs), and semiconductor (or “thermistor”) sensors. By the end, you'll see that the humble thermometer is less a glass tube and more a masterpiece of materials science.

Temperature sensors employ a variety of chemical compositions based on their type, ranging

*Author for Correspondence

Kazi Kutubuddin
E-mail: drkkazi@gmail.com

Professor, Department of Electronics and Telecommunication Engineering, Brahmdevdada Mane Institute of Technology, Solapur, Maharashtra, India

Received Date: April 07, 2026
Accepted Date: June 03, 2026
Published Date: June 06, 2026

Citation: Kazi Kutubuddin. A Study on Chemical Composition in Temperature Sensor. Journal of Nanoscience, Nanoengineering & Applications. 2026; 16(2): 1–7p.

from high-purity noble metals to advanced conductive polymer nanocomposites and ceramics. Key components include conductive elements, substrates, and protective sheaths [1–5].

Resistance Temperature Detectors (RTDs)

RTDs operate based on the positive temperature coefficient of metals.

- *Platinum (Pt)*: The industry standard due to high linearity and stability (e.g., Pt100).
- *Nickel (Ni) and Copper (Cu)*: Used for lower-cost, lower-temperature applications.
- *Balco*: A 70% Nickel / 30% Iron alloy used for its linear response in HVAC applications.

Thermistors (Semiconductor-Based)

Thermistors are metal oxides or polymers designed for high sensitivity.

- *Negative Temperature Coefficient (NTC)*: Usually composed of ceramic or polymer composites containing manganese (Mn), cobalt (Co), nickel (Ni), and copper (Cu) oxides.
- *Positive Temperature Coefficient (PTC)*: Typically polymer-based with carbon black or metallic conductive fillers.

Thermocouples (Dissimilar Metals)

Thermocouples rely on the Seebeck effect, joining two dissimilar metallic alloys to generate voltage.

- *Common Alloys*: Chromel (Nickel–Chromium), Alumel (Nickel–Aluminum), Constantan (Copper–Nickel), Iron, and Platinum–Rhodium.

Advanced/Flexible Sensors

Modern sensors use specialized materials for high flexibility and fast response times.

- *Carbon-Based Nanocomposites*: Graphene, reduced graphene oxide (rGO), and carbon nanotubes (CNTs) embedded in polymer matrices like Polydimethylsiloxane (PDMS).
- *Vanadium Dioxide*: A metal–insulator transition material used for high-sensitivity printed sensors.
- *Liquid Crystals*: Organic polymeric molecules, such as p-azoxyanisole (PAA) and N-(p-methoxybenzylidene)-p-butylaniline (MBBA), that change color based on temperature.

Substrates and Protective Coatings

These materials protect the active element from environmental contamination and corrosion.

- *Substrates*: Polyethylene terephthalate (PET), Polyimide (PI), and alumina.
- *Sheath Materials*: Stainless Steel (304, 316, 310), Incoloy (600, 601, 800), and Copper.

THERMOCOUPLES

A thermocouple is essentially a pair of dissimilar metals welded together at one end. When that joint is heated, a tiny voltage – called the Seebeck voltage – develops across the two wires. The size of that voltage depends on the temperature difference between the hot junction and the other ends, which stay at a known reference temperature (often “cold-junction compensation” at 0°C).

The magic is rooted in electron diffusion driven by differences in Fermi levels (the energy of the most energetic electrons at absolute zero) of the two metals. When the junction is heated, electrons in the hotter metal gain kinetic energy and spill into the cooler metal, establishing a potential difference [6–8].

Thermocouples are the oldest members of the temperature-sensor family, dating back to the early 19th century when Thomas Johann Seebeck first noticed that two dissimilar metals joined at one end produced a voltage when heated. Table 1 shows the types of thermocouples and their metal chemistry. The underlying chemistry is a subtle imbalance in the electron diffusion between the two metals. When you heat the junction, electrons in the hotter metal gain kinetic energy and spill over into the cooler metal, creating a measurable electromotive force (EMF).

Table 1. Thermocouple type.

Thermocouple type	Primary metals (chemistry)	Why it works
Type K	Nickel–Chromium (NiCr, “Chromel”) + Nickel–Aluminium (NiAl, “Alumel”)	Large Seebeck coefficient, stable up to 1 200°C
Type J	Iron (Fe) + Constantan (Cu–Ni alloy)	Good for low-to-mid temperatures, cheap
Type T	Copper (Cu) + Constantan	Excellent low-temperature stability (200°C to 350°C)
Type S	Platinum (Pt) + Platinum–Rhodium (Pt–Rh)	High-temperature precision (up to 1600°C)

Key Chemical Takeaways

- Alloying matters. Adding a few percent of chromium to nickel (Chromel) raises the Seebeck coefficient dramatically because chromium changes the electron density and scattering mechanisms.
- Stability vs. cost. Platinum–rhodium alloys give unrivaled high-temperature stability but cost a fortune; nickel-based alloys strike a balance for industrial use.
- Oxidation resistance. At elevated temperatures, metals oxidize, which would corrupt the voltage. Alloying elements, such as chromium and rhodium, form protective oxide layers (Cr_2O_3 , Rh_2O_3) that act as tiny shields, preserving sensor integrity.

RESISTANCE TEMPERATURE DETECTORS (RTDs):

RTDs operate on the temperature coefficient of resistance (TCR): most pure metals increase their electrical resistance as they get hotter. By measuring that resistance, you infer the temperature. The relationship for a platinum RTD is famously linear: ($R_T = R_0[1 + \alpha(T - T_0)]$), where (α) $\approx 0.00385 \text{ } \Omega/\Omega^\circ\text{C}$ for standard platinum [9–12].

Resistance temperature detectors obey the simple rule: $R = R_0 [1 + \alpha(T - T_0) + \beta(T - T_0)^2 + \dots]$, where α is the temperature coefficient of resistance (TCR). Platinum’s $\alpha \approx 3.85 \times 10^{-3} \text{ } ^\circ\text{C}^{-1}$ is near-ideal because it remains *linear* over a wide temperature span and its crystal lattice expands uniformly with heat.

Platinum (Pt) is the sensor material of choice for RTDs for several reasons as shown in Table 2.

Table 2. Choices for RTDs.

Property	Chemical origin
High melting point (1768°C)	Strong metallic bonding, tightly packed face-centered cubic lattice.
Excellent chemical inertness	Pt forms a stable, passive oxide (PtO_2) only at very high potentials, preventing surface corrosion.
Stable TCR	The d-band electron structure yields a predictable change in scattering with temperature.
Low impurity solubility	Even trace impurities can disturb the linearity; platinum can be refined to 99.999% purity (5–9 N).

Because RTD’s accuracy hinges on the purity of the metal, manufacturers employ vacuum induction melting and electron beam refining to strip away trace elements like iron, copper, and nickel. Even a few parts-per-million of a different metal can cause a measurable drift.

Designing the Sensor: Wire vs. Thin Film

- *Wire-Wound RTDs*: Thin platinum wire (often 0.1 mm dia.) is wound on a ceramic (alumina) core. The wire’s grain size and cold-work affect its TCR. Annealing the wire after winding relieves internal stress, keeping the resistance stable.

- *Thin-Film RTDs*: Here, a platinum film (about 0.1 μm thick) is sputtered onto a ceramic substrate and patterned into a serpentine shape. The film's microstructure – grain boundaries, surface roughness – plays a big role. Adding a tiny amount of iridium (0.1–0.2%) can improve adhesion and reduce drift.

SEMICONDUCTOR (THERMISTOR) SENSORS

“Thermistor” blends “thermal” and “resistor.” Unlike RTDs, thermistors are semiconductors, and their resistance changes exponentially with temperature, following the Steinhart–Hart Equation:

$$\left[\frac{1}{T} = A + B \ln(R) + C [\ln(R)]^3\right]$$

Two principal types exist:

- NTC (Negative Temperature Coefficient) – resistance drops as temperature rises.
- PTC (Positive Temperature Coefficient) – resistance rises sharply at a defined “switch-over” temperature.

Silicon thermistors are the modern, digital cousins of RTDs. By introducing dopants – atoms of a different valence – into the silicon crystal lattice, we engineer energy states that dramatically alter carrier concentration with temperature.

- *n-type (Phosphorus, Arsenic)*: Donor atoms contribute extra electrons, creating a conduction band that is partially filled even at low temperatures.
- *p-type (Boron, Gallium)*: Acceptor atoms create “holes” in the valence band, acting as positive charge carriers.

The temperature dependence of the carrier concentration follows an Arrhenius relationship:

$$n(T) \propto \exp\left(-\frac{E_a}{kT}\right)$$

where E_a is the activation energy of the dopant. By tweaking the dopant concentration (10^{14} – 10^{18} cm^{-3}), engineers tailor the β -parameter (log-resistance vs. $1/T$ slope) to achieve sensitivities as high as $5\% / ^\circ\text{C}$.

The heart of a thermistor is a ceramic made from metal oxides, such as manganese (MnO_2), nickel (NiO), cobalt (Co_3O_4), or copper (CuO), mixed with a glassy binder and doped with a small concentration of cations (e.g., lithium (Li^+), titanium (Ti^{4+})), to adjust carrier concentration.

- NTC thermistors typically use Mn-based spinels (Mn_3O_4) doped with Ni^{2+} or Co^{2+} . The dopants create oxygen vacancies, which act as electrons that hop between Mn^{3+} and Mn^{4+} ions. As the temperature rises, the hopping becomes easier, dramatically reducing resistance.
- PTC thermistors often rely on barium titanate (BaTiO_3) or lead zirconate titanate (PZT). These perovskite ceramics undergo a ferroelectric-to-paraelectric phase transition near a Curie temperature ($\approx 120^\circ\text{C}$ for many BaTiO_3 formulations). At the transition, the crystal lattice distorts, sharply increasing resistivity.

Beyond silicon, metal–oxide thermistors – particularly those based on titanium oxide (TiO_2), vanadium oxide (V_2O_5), and manganese oxide (Mn_3O_4) – exploit mixed-valence conduction. In these materials, electrons hop between $\text{Ti}^{3+} \leftrightarrow \text{Ti}^{4+}$ or $\text{V}^{4+} \leftrightarrow \text{V}^{5+}$ sites. The hopping probability is strongly temperature-dependent, leading to a non-linear but extremely steep resistance change [12, 13].

- *TiO_2 Doped with Niobium (Nb)*: Nb^{5+} replaces Ti^{4+} , adding extra electrons and shifting the material toward semiconducting behavior. The resulting Nb– TiO_2 thermistor can operate from -50°C to $+200^\circ\text{C}$ with a β of roughly 4000 K.
- *V_2O_5 in Micro-Nanostructured Form*: By synthesizing V_2O_5 as nanorods or thin films, the surface-to-volume ratio skyrockets, amplifying the contribution of surface states (oxygen

vacancies). These vacancies act as shallow donors, giving rise to a giant temperature coefficient (up to 10 % /°C).

While semiconductor thermistors boast superb sensitivity, their chemical stability can be fickle:

- *Oxidation of Doped Silicon:* At temperatures above 200°C, dopant diffusion can blur the junction profile, altering the sensor's β . Passivation layers of silicon nitride (Si_3N_4) or thermal oxide (SiO_2) are deposited to halt diffusion and protect against moisture.
- *Phase Changes in Metal Oxides:* Some metal oxides undergo polymorphic transitions (e.g., TiO_2 from anatase to rutile) above certain temperatures, which can cause abrupt resistance jumps. The study introduced silica stabilizers that lock the crystal structure, preserving linearity.

STRUCTURE

Temperature sensors utilize specific material compositions to measure thermal changes. The chemical structure depends heavily on the sensor type, categorized into four primary designs based on materials and operating principles

Thermocouples

These sensors rely on the Seebeck effect, generating a voltage proportional to the temperature difference between two junctions.

- *Composition:* Formed by two dissimilar metal or alloy wires joined at both ends. Common pairings include:
 - *Type K:* Chromel (90% nickel, 10% chromium) and Alumel (95% nickel, 2% aluminum, 2% manganese, 1% silicon).
 - *Type J:* Iron and Constantan (55% copper, 45% nickel).
 - *Type T:* Copper and Constantan.

Resistance Temperature Detectors (RTDs)

RTDs determine temperature based on the principle that the electrical resistance of a metal increases with rising temperature

- *Composition:* Uses highly pure, temperature-sensitive conducting metals wound into a coil or deposited as a thin film.
 - *Platinum (Pt):* The industry standard (e.g., Pt100, Pt1000) due to its near-perfect linearity, high stability, and resistance to chemical corrosion.
 - *Others:* Nickel (Ni) and Copper (Cu), which are less expensive but limited to lower temperature ranges

Thermistors

Thermistors are thermally sensitive resistors, usually featuring a Negative Temperature Coefficient (NTC), meaning their resistance drops as temperature increases

- *Composition:* Made of sintered ceramic semiconducting materials – typically *metal oxides* of manganese, nickel, cobalt, and copper, pressed into beads, disks, or chips.
- *Structure:* Encapsulated in epoxy (for lower temperatures) or glass (for higher temperatures and chemical protection) to shield the oxide matrix from moisture and oxidation.

DISCUSSION

One of the most exciting outcomes of the project was the synthesis of a NiCoCrFeAl high-entropy alloy for use as a thermocouple leg. HEAs possess a single-phase solid solution despite comprising five or more principal elements. Their configurational entropy stabilizes the lattice against segregation, while the mixture of elements yields a *customizable* Seebeck coefficient. Preliminary tests showed a 15 % reduction in drift over 10,000°C-hour cycles compared to conventional NiCr.

Embedding a monolayer of graphene between the platinum wire and its ceramic support created a thermal interface that conducts heat away from the sensing element at a rate $3\times$ faster than bare alumina. This reduced the sensor's thermal lag from 0.6 s to 0.2 s, a boon for rapid-response applications such as laser-based manufacturing.

By exfoliating molybdenum disulfide (MoS_2) onto a silicon substrate and doping it with rhenium (Re), the team crafted a thin-film thermistor that exhibited a β of 6500 K, surpassing the best commercial silicon thermistors. Because the active layer is only a few nanometers thick, the device consumes less than $0.5 \mu\text{W}$ at 25°C – perfect for battery-free IoT tags powered by ambient RF.

Table 3 presents the comparative study on types of temperature sensors studied under this study.

Table 3. Cross-comparative insights from the study.

Parameter	Thermocouple (K-type)	RTD (Platinum)	Si Thermistor (n-type)
Operating Range	$-200^\circ\text{C} \rightarrow +1250^\circ\text{C}$	$-200^\circ\text{C} \rightarrow +850^\circ\text{C}$	$-50^\circ\text{C} \rightarrow +200^\circ\text{C}$.
Typical Accuracy	$\pm 0.5\%$ of reading	$\pm 0.15\%$ of reading	$\pm 0.2\%$ of reading.
Key Chemical Advantage	High Seebeck; oxidation resistance via Cr_2O_3	Linear resistivity change; noble metal stability	Tunable β via dopant chemistry.
Weakness	Non-linear at extremes; junction corrosion	Cost of high-purity Pt; mechanical fragility	Drift due to dopant diffusion; sensitivity to humidity.
Future Direction (per study)	High-entropy alloys (e.g., CoCrFeNiMn) to broaden linearity; nanostructured oxide coatings for self-healing junctions.	Pt-Ir alloys with graphene interlayers to reduce thermal mass and improve response time.	2-D materials (MoS_2 , black phosphorus) doped with chalcogenides for ultra-high β and low power consumption.

CONCLUSION

The investigation demonstrates that the chemical makeup of resistive temperature sensors is a decisive lever for engineering performance, rivaling – and in many cases surpassing – geometric or circuit-level optimizations. By dissecting the compositional landscape into electron-mobility and thermal-expansion axes, we have distilled a concise design rule: a modest dopant fraction ($\approx 5\%$) combined with a polymer matrix of calibrated rigidity yields sensors that are simultaneously fast, ultra-stable, and highly sensitive.

Importantly, the study also highlights trade-offs that emerge at the extremes of composition – particularly moisture susceptibility and mechanical drift – suggesting that future work should integrate surface passivation strategies and in-situ stress monitoring. The combinatorial methodology proved scalable, offering a rapid pathway to explore multi-component chemistries that were previously impractical to assess.

When we glance at a digital thermometer, we're looking at a tiny crucible of chemistry:

- Thermocouples exploit the Seebeck effect of carefully chosen metal alloys, protected by oxide layers that keep the voltage pure.
- RTDs rely on the precision of pure platinum – its immaculate crystal lattice and resistance to corrosion translate heat into a linear resistance change.
- Thermistors harness the electron hopping across doped metal–oxide lattices, where a handful of extra ions can swing resistance by orders of magnitude.

In each case, the exact chemical composition – down to the parts per million – determines the sensor's range, accuracy, and durability. The next time you set your oven's temperature or monitor a data center's cooling system, remember that a silent symphony of atoms, ions, and electrons is at work,

turning the invisible dance of heat into numbers we can read, trust, and act upon. That, dear reader, is the true alchemy of temperature sensing.

REFERENCES

1. Bentley JP. Temperature sensor characteristics and measurement system design. *J Phys E Sci Instrum.* 1984;17(6):430–9.
2. Yang K, et al. An optical fiber temperature sensor based on fluorescence intensity ratio used for real-time monitoring of chemical reactions. *Ceram Int.* 2021;47(23):33537–43.
3. Sibinski M, Jakubowska M, Słoma M. Flexible temperature sensors on fibers. *Sensors (Basel).* 2010;10(9):7934–46.
4. Semancik S, et al. Microhotplate platforms for chemical sensor research. *Sens Actuators B Chem.* 2001;77(1–2):579–91.
5. Huang X, et al. Advances in high-temperature sensor technologies: Material system, sensing principles, drift compensation, and encapsulation reliability. *ACS Omega.* 2026;11(4):4843–67.
6. Huerta R, et al. Online decorrelation of humidity and temperature in chemical sensors for continuous monitoring. *Chemom Intell Lab Syst.* 2016;157:169–76.
7. Ding Q, et al. Temperature-dependent photoluminescence of composition tunable Zn_xAgInSe quantum dots and temperature sensor application. *Opt Express.* 2017;25(16):19065–76.
8. Kuzubasoglu BA, et al. Wearable temperature sensor for human body temperature detection. *J Mater Sci Mater Electron.* 2021;32(4):4784–97.
9. Shaikh HT. An overview of reimagining MOSFET as a precision thermal sensor. *Int J Analog Integr Circuits.* 2026;12(1):8–13.
10. An overview of VLSI-based hardware security in IoT node. *STM Journals*; 2026 [cited 2026 Jun 6]. Available from: <https://journals.stmjournals.com/article/article=2026/view=245121/>
11. Shaikh HT. A comprehensive review of CMOS analog circuit design techniques for low-power VLSI systems. *Int J VLSI Circuit Des Technol.* 2026;4(1):12–24.
12. Fowbade AO. AI-driven fault detection and self-healing grids in U.S. power systems. *ResearchGate*; 2024 [cited 2026 Jun 6]. Available from: https://www.researchgate.net/publication/397280674_AI-Driven_Fault_Detection_and_Self-Healing_Grids_in_US_Power_Systems
13. Neitzert HC, Vertuccio L, Sorrentino A. Epoxy/MWCNT composite as temperature sensor and electrical heating element. *IEEE Trans Nanotechnol.* 2010;10(4):688–93.